## <u>JENWAY</u>

## Flame Photometers

Industrial version supplied with Na, K, Li, Ba & Ca filters



- Flame failure safety system
- Operates on propane, butane, natural gas or L.P.G. supplies
- Fine & coarse sensitivity controls



The Jenway Models PFP7 and PFP7/C are low temperature, single channel flame photometers, designed for the routine determinations of Sodium (Na), Potassium (K), Calcium (Ca), Barium (Ba) and Lithium (Li).

Both versions are fitted with automatic flame failure detection for user safety, making them ideal for use in clinical, industrial or educational applications.



The Model PFP7/C is specifically designed for use in clinical applications. The in-built lineariser circuitry enables readings of both Na and K, at the normal clinical serum concentrations, to be displayed directly in mmol/l. Serum samples must be diluted 200:1 or 100:1 prior to presentation to the flame photometer. Jenway are able to offer the Series 7 Diluter to enable this to be carried out efficiently and accurately.

Model	PFP7	PFP7/C
	(Industrial)	(Clinical)
Ranges	0-199.9	120-160mmol/l Na (linearised)
		0-10.0mmol/lK
Limits of Detection	Na ≤ 0.2ppm	_
	$K \le 0.2ppm$	-
	Li ≤ 0.25ppm	Li ≤ 0.25ppm
	Ca ≤ 15ppm	Ca ≤ 15ppm
	Ba ≤ 30ppm	Ba ≤ 30ppm
Reproducibility	≤1% Coefficient of Variation for 20 consecutive	
	samples using 10ppm Na set to read 50	
Linearity	Better than 2% when concentration of 3ppm	
	Na/K and 5ppm Li are set to read 100	

Electrical: 90-125V or 190-250V @ 50/60Hz Air: moisture and oil free 6 litre/minute @ 1kg/cm<sup>2</sup> (14psi)

Fuel: Propane, Butane, Natural Gas or L.P.G.

Interference from Na/K and Li equal in

Nominal 1.00V for a reading of 100.0

concentration to test element will be <0.5%

Size 420 x 360 x 300mm

Weight 8kg

**Technical Specifications** 

## **Order Codes**

500 701 Model PFP7 supplied with Na, K, Li, Ba & Ca filters, connecting hoses and clips, compressor plug, drain trap, fuses and operating/service instructions. For use on 230V 50Hz.

500 731 Model PFP7 supplied with Na, K, Li, Ba & Ca filters, connecting hoses and clips, compressor plug, drain trap, fuses and operating/service instructions. For use on 110V 60Hz.

500 801 Model PFP7/C supplied with Na, K & Li filters, connecting hoses and clips, compressor plug, drain trap, fuses and operating/service instructions. For use on 230V 50Hz.

500 831 Model PFP7/C supplied with Na, K & Li filters, connecting hoses and clips, compressor plug, drain trap, fuses and operating/service instructions. For use on 110V 60Hz.

## Accessories

Specificity

Services

Recorder Output

Please note: These products will only operate with the correct type of air compressor and gas regulator, as specified.

535 001	Air compressor (220V/50Hz)
535 002	Air compressor (110V/60Hz)
037 001	Series 7 Diluter (230V/50Hz)
037 002	Series 7 Diluter (110V/60Hz)
500 176	Water separator (small)
500 177	Water separator (large)
500 134	Dust cover
500 172	Minor spares kit

Minor spares kit 500 173 Major spares kit 500 178 Butane regulator 500 179 Propane regulator 500 180 Natural gas regulator Cleaning solution 025 016

Clinical Standards (500ml) 025 008 1.00mmol/l Li 100mmol/l Na/K 025 004

140mmol/l Na / 5mmol/l K 025 006 120mmol/l Na / 2mmol/l K 025 007 160mmol/l Na / 8mmol/l K 025 005 160mmol/l Na / 80mmol/l K 025 027

**Industrial Standards (500ml)** 025 023 1000ppm K 025 024 1000ppm Li 025 025 3000ppm Ba 025 021 1000ppm Na 1000ppm Ca 025 009

Jenway Gransmore Green Felsted Dunmow Essex, CM6 3LB, ENGLAND Tel: +44 (0)1371 820122 Fax: +44 (0)1371 821083 e-mail: sales@jenway.com www.jenway.com

Techne Inc. 3 Terri Lane Suite 10 Burlington NJ 08016 USA Tel: 609-589-2560 Fax: 609-589-2571 Toll free: 800 225-9243 www.techneusa.com

Jenway Middle East Overseas Corp. PO Box 27842 Engomi 2433 Nicosia Cyprus Tel: 357 22 660423 Fax: 357 22 660424 e-mail: sales@jenwayme.com

Bibby Scientific (Asia) Ltd Room 607, Yen Sheng Centre 64 Hoi Yuen Road, Kwun Tong Kowloon, Hong Kong Tel: 852 3583 1581 Fax: 852 3583 1580

e-mail: bibby@bibby-scientificasia.com www.bibby-scientificasia.com

